




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>6</sup> : <b>H04L 12/44</b>	<b>A1</b>	(11) International Publication Number: <b>WO 98/36537</b> (43) International Publication Date: <b>20 August 1998 (20.08.98)</b>
(21) International Application Number: <b>PCT/US98/02048</b> (22) International Filing Date: <b>4 February 1998 (04.02.98)</b> (30) Priority Data: <b>08/801,471</b> <b>18 February 1997 (18.02.97)</b> <b>US</b> (71) Applicant: <b>ARCXEL TECHNOLOGIES, INC. [US/US]; Suite 100, 15245 Alton Parkway, Irvine, CA 92618-2307 (US).</b> (72) Inventor: <b>BERMAN, Stuart, B.; 2010 Vista Caudal, Newport Beach, CA 92660 (US).</b> (74) Agents: <b>MURPHY, David, B. et al.; Lyon &amp; Lyon LLP, Suite 4700, 633 West Fifth Street, Los Angeles, CA 90071-2066 (US).</b>		(81) Designated States: <b>CA, JP, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).</b>  <b>Published</b> <i>With international search report.          Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>

**(54) Title: FIBRE CHANNEL SWITCHING FABRIC**



**(57) Abstract**

The Fibre Channel standard was created by the American National Standard for Information Systems (ANSI) X3T11 task group to define a serial I/O channel for interconnecting a number of heterogeneous peripheral devices to computer systems as well as interconnecting the computer systems themselves through optical fibre and copper media at gigabit speeds (i.e., one billion bits per second). Multiple protocols such as SCSI (Small Computer Serial Interface), IP (Internet Protocol), HIPPI, ATM (Asynchronous Transfer Mode) among others can concurrently utilize the same media when mapped over Fibre Channel. A Fibre Channel Fabric is an entity which transmits Fibre Channel frames between connected Node Ports. The Fibre Channel fabric routes the frames based on the destination address as well as other information embedded in the Fibre Channel frame header. Node Ports are attached to the Fibre Channel Fabric through links.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

DESCRIPTION

## FIBRE CHANNEL SWITCHING FABRIC

Field of the Invention

The present invention relates to input/output channel and networking systems, and more particularly to a digital switch which switches Fibre Channel frames at link speeds of up to at least one gigabit per second (i.e., one billion bits per second).

5      Background of the Invention

There is a never ending demand for increased computer system performance. A common limiting factor in computer system performance is the path from the main central processing unit (CPU) to storage, or the I/O path. The CPU usually requires data from attached storage many times faster than the I/O path. Fibre Channel is a standard which addresses this I/O bandwidth limitation.

10      Fibre Channel is an American National Standards Institute (ANSI) set of standards which describes a high performance serial transmission protocol which supports higher level storage and networking protocols such as HIPPI, IPI, SCSI, IP, ATM, FDDI and others. Fibre Channel was created to merge the advantages of channel technology with network technology to create a new I/O interface which

15      meets the requirements of both channel and network users. Channel technology is usually implemented by I/O systems in a closed, structured and predictable environment where network technology usually refers to an open, unstructured and unpredictable environment.

20      Advantages of Fibre Channel include the following. First, it achieves high performance, which is a critical in opening the bandwidth limitations of current computer to storage and computer to computer interfaces at speeds up to 1 gigabit per second or faster. Second, utilizing fiber optic technology, Fibre Channel can overcome traditional I/O channel distance limitations and interconnect devices over

25      distances of 6 miles at gigabit speeds. Third, it is high level protocol independent, enabling Fibre Channel to transport a wide variety of protocols over the same media.

Fourth, Fibre Channel uses fiber optic technology which has very low noise properties. Finally, cabling is simple in that Fibre Channel typically replaces bulky copper cables with small lightweight fiber optic cables.

Fibre Channel supports three different topologies, point-to-point, arbitrated  
5 loop and fabric attached. The point-to-point topology attaches two devices directly. The arbitrated loop topology attaches devices in a loop. The fabric attached topology attaches a device directly to a fabric.

A Fibre Channel fabric is an entity which switches frames between connected devices. Fabric is a word which is synonymous with switch or router. The fabric  
10 must route the frame to the appropriate destination port or return a busy if the port is not available.

Because of the high link speeds, Fibre Channel fabrics face unique problems that are not present in current network switch design. Current network switches which support Ethernet, Fast Ethernet or Asynchronous Transfer Mode (ATM)  
15 protocols route incoming data at speeds up to ten to one hundred times slower than Fibre Channel fabrics. Current network switches also perform some incoming frame validation and network statistics collection. All these network switch features are more difficult to implement when the incoming frame rate is high, as in the case of Fibre Channel.

20 Route determination in network switches is usually performed by microprocessors. The requirement to route frames which are entering the fabric at speeds of up to one gigabit per second requires the fabric to route the frame in very little time. Routing depends not only on the incoming frame address but a host of other parameters and current state conditions as well. There are no currently  
25 available microprocessors which can in real time route sixteen lines of incoming frames with a link speed of 1 gigabit per second.

Frame validation creates another set of problems. In Fibre Channel fabrics frame validation must be performed at rates up to one hundred times faster than in Ethernet switches.

30 Statistics collection is also another function which must be performed in real time. Statistics collected are defined by the Fibre Channel fabric Management

Information Base (MIB) and include the number of frames transmitted and received, the number of fabric rejects and fabric busies transmitted and received, etc. Gathering statistics for sixteen one gigabit per second ports creates new challenges.

Current fabric realizations use either fast microprocessors or digital signal  
5 processors to perform the route determination functions. Typically, processors are single instruction devices which serially decode the instructions and perform the specified function. Digital signal processors contain parallel functions and can perform several functions at one time. Still the problem exists to determine the route for many simultaneous incoming frames at one gigabit per second. Current fabric  
10 implementations perform routing on the order of tens of microseconds to hundreds of milliseconds. Ideally, routing should be accomplished in less than one microsecond.

Another problem with fabric realization is the support of the Arbitrated Loop topology. This topology has unique characteristics and requirements. Current fabric implementations do not support this topology.

15 Efficient support of both connection based classes of service (i.e., Class 1) and connectionless classes of service (i.e., Class 2 and 3) is also a challenge. A fabric must implement a different type of switch core to implement each class of service. Coordination between the different switch cores can be a burdensome task. Current fabric implementations support either a connection based or a connectionless switch  
20 core. This leads to inefficiencies, e.g., a connectionless switch core cannot switch Class 1 traffic if routes are not determined in frame time (i.e., less than one microsecond) and a connection switch core is very inefficient when routing Class 2 and Class 3 traffic.

Another problem with fabric realization is the interconnection or networking  
25 of fabrics. This is a problem due to the high speeds involved. Determining a network route is sometimes even more difficult than determining a local route. Destination addresses must be matched based not only on all bits matching but also matching a portion of the address. Route priorities should also be implemented to allow backup routes to a destination.

### Summary of the Invention

The present invention described and disclosed herein comprises a method and apparatus for transporting Fibre Channel frames between attached devices. The apparatus comprises logic which supports but is not limited to the following features:

- 5 Transport of Class 1, Class 2 and Class 3 frames, Support for the Arbitrated Loop topology on each link, Support for Fabric point-to-point topology on each link, Route determination in frame arrival time, and Interconnection or Networking of Fabrics.

In one aspect of the invention, the apparatus comprises separate port control modules, one for each attached device, a central router module, a switch core module,  
10 a fabric control module and a brouter (bridge/router) module. In the preferred embodiment, the port control modules are connected to the router modules by separate route request connections and separate route response connections. Through this structure, route requests may be provided from the port control module to the router while simultaneously the router provides route request responses to the same  
15 port control module. Preferably, a common route request channel is utilized. Thus, apparatus is provided to return a route response to a previously requesting port while other ports are arbitrating and sending route requests to the centralized router. More generally, this apparatus provides for reading resource requests from multiple requesters while at the same time returning resource grant responses to previous  
20 requesters.

The router of the subject invention includes many advantageous aspects. In the preferred embodiment, the router includes multiple state machines arranged in series for pipeline operation. Specifically, in the preferred embodiment of the router, a hardware finite state machine operates on the route request and a hardware finite  
25 state machine provides the route response. Thus, in this embodiment, the router includes an input for receiving the output of the route request generator of the port control module, an output for sending a route request response to the route request response receiver in the port control module, a hardware finite state machine to receive the route request, and a hardware finite state machine to provide the route  
30 response, in combination with a route determination system. Through implementation

in hardware, route responses may be made in less than two microseconds, which permits essentially real-time routing at gigahertz frequencies.

In yet another aspect of the router, it routes Fibre Channel frames to a destination port on the Fabric based on a selected portion of the incoming frame's destination address. In the preferred embodiment, Fibre Channel FCPH protocol rules are applied to an incoming frame to determine whether to route the frame or return a fabric reject or busy frames or to discard the frame. Validation of the routing of a Fibre Channel frame is based on the rules defined in the ANSI FCPH standards. In the preferred embodiment, route requests are serviced in a round robin manner from multiple ports.

In another embodiment an apparatus and method is provided to store blocked route requests until either the blocking condition resolves itself or a specified time period expires. Thus, a method for servicing route request from multiple attached devices where the routing is subject to blocked and unblocked conditions may be effective, where the method comprises the steps of servicing a route request which is not blocked, but saving a blocked route request in hardware, preferably in registers, and then servicing that request if the route changes from a blocked to an unblocked condition, in the preferred embodiment, prior to the expiration of a specified time period. In a more general sense, the invention manages the blocking and unblocking of multiple resource requests to a central resource.

In another embodiment an apparatus is provided to handle the scenario when a port input fifo is going to overflow with an incoming Fibre Channel frame. Generally, the incoming data stream is typically provided to an encoder/decoder, from which it is supplied to a buffer. In the event of a data overrun condition to the buffer, overrun prevention logic causes the setting of tag bits to a condition which may be recognized downstream as indicative of a buffer overflow condition.

In another embodiment an apparatus is provided to interleave accesses by the processor on the outgoing port bus in between outgoing frames or when the output fifo is full.

In another embodiment an apparatus is provided to pack requests in a register array in order of first arrival but allow the removal of the requests from anywhere in the array.

#### Objects of the Invention

5           It is an object of this invention to provide a fibre channel fabric capable of operating at at least 1 gigabit speeds.

          It is yet a further object of this invention to permit the establishment of a path through a fabric in real time at gigabit speeds.

10           It is yet a further object of this invention to provide 1 microsecond or less response time to fibre channel frames.

          It is another object of this invention to determine in real time at gigabit speeds that no through path can be established through the fabric.

          It is yet another object of this invention to provide a fibre channel fabric capable of simultaneously supporting Class 1, Class 2 and Class 3 service.

15           It is an object of this invention to provide a fibre channel switching fabric which supports arbitrated loop topology.

          It is yet another object of this invention to provide systems and methods adapted for interconnection of multiple fabrics.

20           It is yet another object of this invention to provide a system which supports Fabric point-to-point topology on each link.

#### Brief Description of the Drawings

FIG. 1 is a diagram illustrating the use of a Fibre Channel Fabric.

FIG. 2 is a block diagram of a Fibre Channel Fabric.

FIG. 3 is a block diagram of the Fabric Control module.

25           FIG. 4 is a block diagram of the fabric Router.

FIG. 5 is a block diagram of the fabric Port Control.

FIG. 6 is a block diagram of the fabric Switch core

FIG. 7 is a block diagram of the Brouter Module.

FIG. 8 is a diagram of the Port Control FIFO Overrun Prevention Logic.

FIG. 9 is a diagram of the Port Control Process to Endec Arbitration Logic.

FIG. 10 is a more detailed description of the Port Control module.

FIG. 11 is a diagram of the main Port Control FSM.

FIG. 12 is a diagram of the Port Control PCFIFO module interface signals.

5 FIG. 13 is a diagram of the Router address matching module.

FIG. 14 is a diagram of the Router Route Request Unblock Determination module.

FIG. 15 is a detailed diagram of the Route Request Unblock Determination module circuit.

10 FIG. 16 is another detailed diagram of the Route Request Unblock Determination module circuit.

FIG. 17 is a diagram of the Blocked Route Request Table.

FIG. 18 is a diagram of the Router Control State Machine.

FIG. 19 is a diagram of the Blocked Route Request Port Register Array.

15 FIG. 20 is a diagram of both the Route State Table and the Route Determination modules.

FIG. 21 is a more detailed diagram of the Route Determination module.

FIG. 22 is a another more detailed diagram of the Route Determination module.

20 FIG. 23 is a still another more detailed diagram of the Route Determination module.

FIG. 24 is a diagram of the Port Control Route Request Interface module.

FIG. 25 is a diagram of the Port Control Route Response Interface module.

25 FIG. 26 is a diagram of the Router to Port Control Route Request State Machine.

FIG. 27 is a diagram of the Router to Port Control Route Response State Machine.

FIG. 28 is a diagram of the Port Control to Router Interface State Machine.

FIG. 29 is a diagram of the Hub Port Control module.

30 FIG. 30 is a diagram of the format of the Blocked Route Request Table entry.

FIG. 31 is a diagram of the format of the Route Request.

FIG. 32 is a diagram of the format of the Router to Port Control Response.

FIG. 33 is a diagram of the format of the Address Table entry.

FIG. 34 is a diagram of the format of the Route State Table entry.

5	<u>Detailed Description of the Invention</u>
	<u>Table of Contents</u>
	A. Definitions
	B. Fibre Channel Fabric Model
	C. Fabric Control Module
10	D. Fabric Router
	1. Port Control Route Request Interface Module
	2. Port Control Route Response Interface Module
	3. Address Table
	4. Address Match Module
15	5. Blocked Route Request Table
	6. Blocked Route Request Port Register Array
	7. Blocked Route Request Timer
	8. Route Request Unblock Determination Module
	9. Route Request Selector
20	10. Route Determination Module
	11. Route State Table
	12. Router Statistics Gathering Module
	13. Router Control FSM
	E. Port Control
25	1. Port Control Module
	2. FIFO Overrun Prevention Logic
	3. Processor/Data Arbitration Logic
	4. Port Control Hub Module
	F. Switch Core
30	G. Router Module

## H. Other Documents

### A. Definitions

For expository convenience, the present invention is referred to as the Fibre Channel Fabric or Fabric, the lexicon being devoid of a succinct descriptive name for  
5 a system of the type hereinafter described.

The "Fibre Channel ANSI standard" describes the physical interface, transmission protocol and signaling protocol of a high-performance serial link for support of the higher level protocols associated with HIPPI, IPI, SCSI, IP, ATM and others.

10 The "Fibre Channel Fabric" comprises hardware and software that switches Fibre Channel frames between attached devices at speeds up to one gigabit per second.

The following discussions will be made clearer by a brief review of the relevant terminology as it is typically (but not exclusively) used.

15 "Fibre Channel" is an American National Standard for Information Systems (ANSI) standard which defines a high performance serial link for support of the higher level protocols associated with HIPPI, IPI, SCSI, IP, ATM, FDDI and others.

"FC-1" defines the Fibre Channel transmission protocol which includes the serial encoding, decoding, and error control.

20 "FC-2" defines the signaling protocol which includes the frame structure and byte sequences.

"FC-3" defines a set of services which are common across multiple ports of a node.

25 "FC-4" is the highest level in the Fibre Channel standards set. It defines the mapping between the lower levels of the Fibre Channel and the IPI and SCSI command sets, the HIPPI data framing, IP, and other Upper Level Protocols (ULPs).

"Fibre" is a general term used to cover all transmission media specified in the ANSI X3.230 "Fibre Channel Physical and Signaling Interface (FC-PH)" standard.

A "fabric" is an entity which interconnects various N\_Ports attached to it and is capable of routing frames by using only the D\_ID information in the FC-2 frame header. The word Fabric can be seen as a synonym with the word switch or router.

5 "Fabric topology" is a topology that uses the Destination Identifier (D\_ID) embedded in the Frame Header to route the frame through a Fabric to the desired destination N\_Port.

"Point-to-point topology" allows communication between N\_Ports without the use of a Fabric.

10 A "circuit" is a bidirectional path that allows communication between two L\_Ports.

"Arbitrated Loop topology" permits three or more L\_Ports to using arbitration to establish a point-to-point circuit. When two L\_Ports are communicating, the arbitrated loop topology supports simultaneous, symmetrical bidirectional flow.

15 "Link Control Facility" is a facility which attaches to an end of a link and manages transmission and reception of data. It is contained within each Port type.

"Port" is a generic reference to an N\_Port or F\_Port.

An "N\_Port" is a hardware entity which includes a Link Control Facility.

An "NL\_Port" is an N\_Port that contains Arbitrated Loop functions associated with Arbitrated Loop topology.

20 An "F\_Port" is a generic reference to an F\_Port or FL\_Port.

An "FL\_Port" is an F\_Port that contains Arbitrated Loop functions associated with Arbitrated Loop topology.

An "L\_Port" is an N\_Port or F\_Port that contains Arbitrated Loop functions associated with Arbitrated Loop topology.

25 A "Node" is a collection of one or more N\_Ports controlled by a level above FC-2.

A "dedicated connection" is a communicating circuit guaranteed and retained by the Fabric for two given N\_Ports.

30 A "connection" is the process of creating a Dedicated Connection between two N\_Ports.

A "disconnection" is the process of removing a Dedicated Connection between two N\_Ports.

A "frame" is an indivisible unit of information used by FC-2.

"Frame content" is the information contained in a frame between its Start-of-Frame and End-of-Frame delimiters, excluding the delimiters.

A "data frame" is a frame containing information meant for FC-4/ULP or the Link application.

"Payload" is the contents of the Data Field of a frame, excluding Optional Headers and fill bytes, if present.

"Source Identifier" or S\_ID is the address identifier used to indicate the source Port of the transmitted frame.

"Destination Identifier" or D\_ID is the address identifier used to indicate the targeted destination of the transmitted frame.

"Valid frame" is a frame received with a valid Start of Frame (SOF), a valid End of Frame (EOF), valid Data Characters, and proper Cyclic Redundancy Check (CRC) of the Frame Header and Data Field.

"Classes of Service" are different types of services provided by the Fabric and used by the communicating N\_Ports.

"Class 1" service is a service which establishes a dedicated connection between communicating N\_Ports.

"Class 2" service is a service which multiplexes frames at frame boundaries to or from one or more N\_Ports with acknowledgement provided.

"Class 3" service is a service which multiplexes frames at frame boundaries to or from one or more N\_Ports without acknowledgement.

"Intermix" is a service which interleaves Class 2 and Class 3 frames on an established Class 1 connection.

A "Gigabit Link Module" is a module which interfaces to the Endec through either a 10-bit or 20-bit interface and interfaces to the Fibre Channel link through either a copper or fiber interface.

An "Encoder/Decoder" or Endec is a device which implements the FC-1 layer protocol.

A "Router" is a module which determines the destination port from an address and other Fibre Channel frame parameters.

A "Port Control" is a module which reads in a Fibre Channel header, requests a route and forwards the frame to the switch core.

5        "Credit" is the login credit which represents the number of frames that may be transmitted before receiving an acknowledgement or R\_RDY.

"Fabric Login Protocol" is when an N\_Port interchanges Service Parameters with the Fabric by explicitly performing the Fabric Login protocol or implicitly through an equivalent method not defined in FC-PH.

10        "Application Specific Integrated Circuit" or (ASIC), an integrated circuit designed to perform a particular function by defining the interconnection of a set of basic circuit building blocks drawn from a library provided by the circuit manufacturer.

15        "FPGA" Field Programmable Gate Array, a gate array where the logic network can be programmed into the device after its manufacture. An FPGA consists of an array of logic elements, either gates or lookup table RAMs, flip-flops and programmable interconnect wiring. Most FPGAs are dynamically reprogrammable, since their logic functions and interconnect are defined by RAM cells.

20        "FIFO" a data structure or hardware buffer from which items are taken out in the same order they were put in.

"Bridge" a device which forwards traffic between network segments based on datalink layer information. These segments would have a common network layer address.

25        "Router" a device which forwards traffic between networks. The forwarding decision is based on network layer information and routing tables, often constructed by routing protocols.

"Brouter" a device which bridges some packets (i.e. forwards based on datalink layer information) and routes other packets (i.e. forwards based on network layer information). The bridge/route decision is based on configuration information.

30        "Hub" a device connecting several other devices.

“Serdes” serial encoder/decoder, converts the Fibre Channel serial interface to/from a 10 or 20 bit parallel interface.

“HIPPI” is a computer bus for use over fairly short distances at speeds of 800 and 1600 megabytes per second. HIPPI is described by the ANSI standard X3T9/88-  
5 127.

“SCSI” or Small Computer System Interface is a standard for system-level interfacing between a computer and intelligent devices including hard disks, tape drives, and many more. SCSI is described by the ANSI standard X3.131-1986 and by ISO/IEC 9316.

10 “ATM” or Asynchronous Transfer Mode is a method for the dynamic allocation of bandwidth using a fixed-size packet, also called a cell.

“SNMP” or Simple Network Management Protocol is an Internet Standard protocol defined in RFC 1157, developed to manage nodes on an IP network.

“MIB” or management information base is a database of managed objects  
15 accessed by network management protocols such as SNMP.

“Web” is the World-Wide Web, an Internet client-server distributed information retrieval system which originated from the CERN High-Energy Physics Laboratories in Geneva, Switzerland.

“Web Browser” is a program which allows a person to read information from  
20 the Web. The browser gives some means of viewing the contents of nodes (or “pages”) and of navigating from one node to another.

#### B. Fibre Channel Fabric Model

Referring to Fig. 1, a Fibre Channel Fabric is an entity which transports Fibre Channel frames between attached devices. The data transmission between the  
25 connected device port (i.e., N\_Port) and the Fabric port (i.e., F\_Port) is serial and consists of one or more frames. The transmission protocol and speeds along with the fabric functionality are defined in the American National Standard for Information Systems (ANSI) FCPH standard (see Other documents, section H, below).

The primary function of the Fabric is to receive frames from a source N\_Port  
30 and route the frames to the destination N\_Port whose address identifier is specified

in the frames. Each N\_Port is physically attached through a link to the Fabric or in the case of an Arbitrated Loop topology attached to the same loop. FC-2 specifies the protocol between the Fabric and the attached N\_Ports. A Fabric is characterized by a single address space in which every N\_Port has a unique N\_Port identifier.

5           The Fabric model contains three or more F\_Ports or FL\_Ports. Each F\_Port is attached to an N\_Port through a link. Each F\_Port is bidirectional and supports one or more communication models. The receiving F\_Port responds to the sending N\_Port according to the FC-2 protocol. The Fabric optionally verifies the validity of the frame as it passes through the Fabric. The Fabric routes the frame to the F\_Port  
10           directly attached to the destination N\_Port based on the N\_Port identifier (D\_ID) embedded in the frame. The address translation and the routing mechanisms within the Fabric are transparent to N\_Ports.

          There are two Sub-Fabric models, a Connection based model and a Connectionless based model. The Connection based Sub-Fabric provides Dedicated  
15           Connections between F\_Ports and the N\_Ports attached to these F\_Ports. A Dedicated Connection is retained until a removal request is received from one of the communicating N\_Ports or an exception condition occurs which causes the Fabric to remove the Connection. The Connection based Sub-Fabric is not involved in flow control which is managed end-to-end by the N\_Ports. If the Fabric is unable to  
20           establish a Dedicated Connection, it returns a busy or reject frame with a reason code.

          A Connectionless Sub-Fabric is characterized by the absence of Dedicated Connections. The Connectionless Sub-Fabric multiplexes frames at frame boundaries between an F\_Port and any other F\_Port and between the N\_Ports attached to them.

          A given frame flows through the Connectionless Sub-Fabric for the duration  
25           of the routing. After the frame is routed, the Connectionless Sub-Fabric is not required to have memory of source, routing or destination of the frame. When frames from multiple N\_Ports are targeted for the same destination N\_Port in Class 2 or Class 3, congestion of frames may occur within the Fabric. Management of this congestion is part of the Connectionless Sub-Fabric and buffer-to-buffer flow control.

30           FIG. 1 shows a possible environment containing a Fibre Channel fabric. The fabric 1, 2 illustrated are connected with a mix of workstations 3, disk arrays 4,

mainframe computers 5, and Personal Computers (PC) 6. Fabric interconnection is not limited to particular equipment or a network topology as illustrated in FIG. 1. Two types of fabric topologies are illustrated in FIG. 1., the direct fabric attached topology 9 and the arbitrated loop topology 7.

5           The fabrics in FIG. 1 are shown interconnected or networked through a link 8. All links to the fabric can operate at either 266 Mbps, 533Mbps or 1.063 Gbps speeds and operate over either copper or fiber media, or any other compatible media..

FIG. 2 shows a block diagram of the fabric. The fabric is composed of a fabric control module 54, a router module 52, multiple port control modules 51, 74,  
10       75 a switch core module 53 and optionally one or more brouter modules 55. As is understood in the art, the functions allocated to these respective devices may, in alternate embodiments, be allocated to different logical blocks.

The fabric control module 54 contains a processor and associated hardware. The fabric control module software performs but is not limited to the following  
15       functions: (1) Fabric power on self test, (2) Fabric configuration, (3) Broadcast, Simple Name, ARP and Directory services servers, (4) Fabric Loop Attached profile Extended link service command, (5) Management, (6) Network Management SNMP agent, (7) Web based fabric management, (8) Uninterruptable power supply monitoring and control, and (9) Brouter Module Configuration/Control. The Fabric  
20       Control module controls and configures the rest of the fabric but is not usually involved in the normal routing of frames.

The fabric Router 52 performs some or all of the following functions: (1) route address matching, (2) route determination based on the ANSI X3T11 rules, (3) route request blocking and unblocking, (4) switch core programming 63, (5) statistics  
25       collection and (6) port control module route request/response handling 59, 60, 61, 62, 66, 67, 72, 73.

The fabric Port Control modules (PCM) 51, 70, 74, 75 perform some or all of the following functions: (1) receive Fibre Channel frames from the fiber or copper media 56, 77, 78, (2) perform frame validation, (3) send a route request to the router  
30       59, 61, 66, 72, (4) receives a route response from the router 60, 62, 63, 67, 73, (4) forwards the frame to the switch core 57, 69, and (5) either discards the frame,

modifies the frame into a fabric reject (F\_RJT) or fabric busy (F\_BSY) frame or forwards the frame depending on the route response from the router.

The fabric switch core 53 is a nonblocking NxN matrix switch with 36 bit wide transmit and receive I/Os. The switch core switches frames from the PCMs 51, 70, 74, 75 to the destination PCMs or Brouter Module.

The Brouter Module 55 performs some or all of the following functions: protocol bridging and/or routing function between a Fibre Channel network and the network implemented by the Brouter Module. The Brouter Module "looks" like a Fibre Channel port to the rest of the switch. This is due to a protocol conversion function in the Brouter Module which converts the brouter networked frames to Fibre Channel frames. Converted Fibre Channel frames from the Brouter Module enter the fabric switch through an internal port control module 70. Fibre Channel frames from the fabric switch core enter the Brouter Module through an internal path 76.

### C. Fabric Control Module

FIG. 2 shows the Fabric Control module (FCM) 54. The FCM 54 serves some or all of the following functions: configures the fabric, collects and reports network management parameters and implements the fabric defined servers such as the Simple Name Server, Directory Services, etc. The FCM 54 configures the router 52, the port control modules 51, 74, 75 and the brouter module 55.

FIG. 3 shows the Fabric Control module (FCM) in more detail. The FCM is made up preferably of fast SRAM 82, DRAM 83, a DUART 84, flash memory 85 (nonvolatile storage), a processor 81 and a Decode/DMA Control module 87. The code for the processor is contained in the flash memory 85 and is copied to SRAM upon bootup. The interface to the brouter module 55 allows the FCM to communicate through legacy networks such as ethernet and fast ethernet, depending on the brouter module.

The FCM is attached to the rest of the fabric in two different manners: both in-band 80 to the fabric and out of band 79 to the fabric. The in-band connection is through the internal port control module. This connection allows the Fabric Control Module to communicate with both locally and remotely attached Fibre Channel

compliant devices via Fibre Channel frames. The FCM connects out of band to the rest of the system for monitoring, initialization and control reasons.

#### D. Fabric Router

The Fabric Router 52 (FIG. 2) receives route requests generated from the Port Control modules 59, 61, 66, 72, determines the frame route, reports the route responses to the Port Control modules 60, 62, 67, 73, programs the switch core to connect and disconnect the routes 63, manages blocked route requests and collects the routing statistics. In the preferred embodiment, there is one central router contained in a fabric. The Router 52 connects and disconnects routes on a frame by frame basis. Since the router can determine a route in real time (i.e., Fibre Channel frame time) the Fabric can support Class 1 frames. The router is realized in hardware through either an FPGA or a custom ASIC. The router is composed of thirteen functional modules as illustrated in FIG. 4:

- (1) Port Control Route Request Interface (PCRRIM) 130
- (2) Port Control Route Response Interface (PCRSPM) 144
- (3) Address Table 132
- (4) Address Match Module (ADM) 131
- (5) Blocked Route Request Table Module (BRTBL) 133
- (6) Blocked Route Request Port Register Array (BRRRA) 134
- (7) Blocked Route Request Timer (BRTMR) 135
- (8) Route Request Unblock Determination Module (RRUNB) 136
- (9) Route Request Selector (RRS) 137
- (10) Route Determination Module (RDM) 138
- (11) Route State Table (RST) 139
- (12) Router Statistics Gathering Module (RST) 141
- (13) Router Control FSM (RCFSM) 140.

#### 1. Port Control Route Request Interface Module (PCRRIM)

The Port Control Route Request Interface Module (PCRRIM) 130 of FIG. 4 (and FIG. 24 numeral 581) interfaces with the PCMs (51, 74, 75 of FIG. 2) to read

route requests and registers the route request for use by the internal router modules. The PCRRIM FIG. 24 is composed of the following functional blocks: round-robin arbitration 582, route request state machine 583, registered route request 584, and the port winning arbitration register 585. The PCRRIM 581 is connected to each PCM (items 56, 77 and 78 of FIG. 4) through a separate PCM requester signal 586. The PCRRIM 581 is also connected to each PCM through a common shared route request data channel 588. After a PCM captures an incoming frame and builds a route request the PCM raises the PCM route request signal 586. The PCRRIM round robin arbitration block 582 will read all request signals and choose the requester in a round robin manner. This implements requester fairness, i.e., one requester will not be able to starve other concurrent PCM requesters. The round robin arbitration block 582 will notify the winning PCM requester via the route request state machine 583 by pulsing for one clock period the PCM acknowledge signal 587 back to the winning PCM. During the next four clocks the PCM sends the route request over the common route request channel 588 to the registered route request block 584. The Route Request channel is implemented as an eight bit bus, but is not restricted to that size. The route request is thirty two bits and is shown in FIG. 31. The signals are described below.

20	<u>Route Request</u> <u>Field</u>	<u>Description</u>
	SID Mismatch	Indicates that the incoming frame SID does not match the expected SID
	EOFrcvd	Indicates that the entire frame including the EOF was received
	Route Direct	A flag to override the router address matching logic. This is used to route frames from the fabric control module out to a specific port without the use of the DID field
	Delimiter	Is an encoded field which specifies the received frames delimiter
25	Destination Address	The DID from the incoming frame. This field is valid only when the route direct flag is not set.
	Destination port to route to	Only valid when the route direct flag is set, indicates the remote port to route the frame to.

The winning PCM port number is registered 585 (FIG. 24) and held for use by the internal router modules 589. The PCRRIM is controlled by the Router Control FSM through the request serviced signal 591. The PCRRIM will raise the request valid signal 590 whenever it has a valid route request from a PCM in its register 584.

5 The PCRRIM will halt any further route request reads from the PCM until the request serviced signal 591 is pulsed for one clock period by the Router Control FSM.

FIG. 26 shows the PCRRIM state machine. The state machine is described below.

	<u>State</u>	<u>Description</u>
10	IDLE 611 CMP_RR_VECT 612	Wait for a route request from a port control Route robin logic, compare the current select vector with the port control. If a match occurs the port control is currently requesting a route.
	SHIRT_RR_VECT 613 WAITCLK 614	Shift the current select vector. Signal the select port control module, wait one clock before reading the route request channel for the route request.
15	LDWORD0,1,2,3 615,616,617,618	Read the route request from the route request channel. Since the route request channel is 8 bits wide and the route request is thirty two bits, four clocks are needed to read the route request.
	RTNAVAIL 619	Wait until the Main Route Control FSM signals that the route request is no longer needed (RTACK) then return to idle and wait for another route request from the port control modules.

## 2. Port Control Route Response Interface Module (PCRSPM)

As shown in FIG. 4 the Port Control Route Response Interface Module (PCRSPM) 144 interfaces with all the PCMs 114, the Route Determination module

20 138 and the Router Control FSM module 140. The PCRSPM main function is to return route responses to the PCMs 114. The PCRSPM 144 is independent of the PCRRIM 101 which enables the router 52 to concurrently receive route requests and send route responses. This separation in function adds parallelism to the router, permits pipelined operation of the router and increases its performance.

As shown in FIG. 25 the PCRSPM is preferably composed of the following functional blocks: the route response state machine 602 and the route response register 603. The PCRSPM registers the route response 608 from the Route Determination module when the load route response signal 607 is pulsed for one clock period by the Router Control FSM 140 (FIG. 4). When the Router Control FSM 140 pulses the send route response signal 606 the route response state machine 602 will inform the PCM corresponding to the port vector 609 by pulsing the PCM response acknowledgement signal 604 and putting the route response on the common route response channel 605 for the next four clocks. FIG. 32 shows the thirty two bit route response format. An eight bit common route response channel is shown but a thirty two bit wide channel can be used depending on the implementation.

FIG. 27 shows the PCRSPM state machine (item 602 of FIG. 25). The state machine is described below.

	<u>State</u>	<u>Description</u>
15	IDLE 631	Wait for main Router Control FSM to assert the return route response signal.
	XMTRSP 632	Acknowledge the main Router Control FSM that the route response will be returned. Signal the specific port control module the route response will be on the route response data channel on the next two clocks.
	XMT_DT0 633	Load the first eight bits of the route response on the route response data channel.
	XMT_DT1 634	Load the second eight bits of the route response on the route response data channel, return to IDLE.

### 3. Address Table

The Address Table 132 of FIG. 4 is initially configured by the processor in the fabric control module 122. The Address Table 132 contains entries against which the incoming Fibre Channel frame destination identifier (D\_ID) is compared. FIG. 33 shows the preferred address table entry format. The address entry contains a twenty four bit address mask register along with a twenty four bit address register. The incoming D\_ID is ANDed with the address mask register and the result is compared to the address register. This allows a match to be performed on any

number of bits in the address. This also implements routing based on any combination of the address domain (upper eight bits of the address field), area (middle eight bits of the address field) or port (lower eight bits of the address field) fields. Additional address fields include the destination port and the address priority fields.

- 5 The destination port indicates which remote F\_Port to route the frame to and the address priority field specifies a priority for this address table entry match. For any two address matches the address table entry match which is the highest priority will be used. This implements an alternate routing in case of port failure.

#### 4. Address Match Module (ADM)

- 10 The Address Match module 13 (ADM) in FIG. 4 (FIG. 13 numeral 351) performs the comparison with the incoming frame D\_ID address from the route request 105 with the Address Table contents 109. The results are used by the Route determination module 138. As shown in FIG. 13 the ADM 351 has as an input the twenty-four bit address to match 352, i.e., the incoming frame D\_ID address from the
- 15 route request, and returns the following responses: the remote match port 354, the address matched indication 355 and the route to control module indication 353. The ADM will match an incoming D\_ID address to all the addresses in the address table in one clock. The ADM logic is implemented in combinatorial logic. The ADM performs the following checks for each address table entry:

- 20 Address Match indication = (address in table == (address mask & D\_ID))

- The results are then priority decoded based on address priority contained in the address table and the resulting address match signal and port are generated. There is one special mode which is implemented which will preemptively route all frames to the Fabric Control module except frames originating from the Fabric Control
- 25 module. This allows the fabric control module to process all incoming frames which is useful when the fabric is functioning in certain environments.

#### 5. Blocked Route Request Table (BRTBL)

The Blocked Route Request Table 133 (BRTBL) in FIG. 4 functions to save blocked route requests. Preferably, it is realized by an array of registers. The

BRTBL saves enough information to regenerate the route request once the blocking condition is cleared. The format of the blocked route request is shown in FIG. 30. The blocked route request contains the requesting PCM port, the matched destination PCM port, the block reason, whether an EOF delimiter was received by the requesting PCM, i.e., whether the entire frame was received before the PCM requested a route, the delimiter in the incoming frame, i.e., SOF type, whether there was an address match, whether to route to the fabric control port and whether a fabric reject (F\_RJT) or fabric busy (F\_BSY) should be generated.

As shown in FIG. 4 the BRTBL reads the blocked route request from route request bus 107 when instructed to do so by the Route Control FSM 140. As shown in FIG. 17 a blocked route request is loaded upon a LOADFIFO 447 signal pulse by the Router Control FSM. Blocked route requests are cleared when the CLR\_FIFO 448 signal is pulsed by the Router Control FSM. The port input vector, 449, selects which port location in the table to load or clear the blocked route request. There is one blocked route request entry for each PCM and the blocked route request is registered so certain fields are available FIG. 4 numeral 116 to the Route Request Unblock Determination module FIG. 4 numeral 136. As shown in FIG. 17, the BRTBL 441 contains the registered blocked route request table 442 so certain fields in the blocked route request can be monitored by other router internal modules, 443, 444, 445, 446. The signals which are monitored include whether the specific entry contains a blocked route request 444, the block reason 443 which includes blocked due to the remote port busy or blocked due to the remote port in a class 1 connection with a port other than this one, and intermix is not support by the remote port. Other monitored fields include whether the blocked request frame is a Class 1 frame as indicated by the SOF delimiter.

#### 6. Blocked Route Request Port Register Array (BRRA)

The Blocked Route Request Port Register Array 134 (BRRA) in FIG. 4 reads in the requesting port 103 and saves it into a register array which keeps the PCM request order. This order is wired 118 to the Route Request Unblock Determination module 136. The BRRA is shown in more detail in FIG. 19. When the LOADFIFO

483 signal from the Router Control FSM is pulsed for one clock period the requesting PCM port 482 is saved into position 0 numeral 489 of the register array. Register array entries are removed by the Route Request Unblock Determination module through the CLRFIFO 488 signal and DEQRQ\_SEL 485 vector, i.e., when the

5 CLRFIFO signal is pulsed for one clock period the BRRA will unload the register specified by the DEQRQ\_SEL vector.

Position 0 numeral 489 contains the newest route request and position 16 numeral 490 contains the oldest route request. Register array contents are shifted by one, from the newest position to the oldest, when the LOADFIFO signal is pulsed to

10 make room for the newest blocked route request port number. The shifting circuit must take into account 'holes' in the register array. The algorithm identifies the first free register array entry closest to position 0 and shifts all the entries from position 0 to the free register array entry. The shifting circuit creates a shift vector (STTMP) which is used to load the contents of the individual register array entries. The circuit

15 is shown below in verilog for eight ports.

```

always @(F1_NULL or F2_NULL or F3_NULL or F4_NULL or F5_NULL
or F6_NULL or F7_NULL or F8_NULL) begin

    // build fifo shift control word (indicates how to shift fifo)
    casex ({F8_NULL, F7_NULL, F6_NULL, F5_NULL,
            F4_NULL, F3_NULL, F2_NULL, F1_NULL})
        8'b1xxxxxxx: STTMP = 8'b11111111;
        8'b01xxxxxx: STTMP = 8'b01111111;
        8'b001xxxxx: STTMP = 8'b00111111;
        8'b0001xxxx: STTMP = 8'b00011111;
        8'b00001xxx: STTMP = 8'b00001111;
        8'b000001xx: STTMP = 8'b00000111;
        8'b0000001x: STTMP = 8'b00000011;
        8'b00000001: STTMP = 8'b00000001;
        default: STTMP = 8'b00000000;
    endcase
end // always

where F1_NULL, ..., F8_NULL are true if register array position 1 to 8
(respectively) are empty.

```

The shifting vector is then used with the CLR\_FIFO signal 484 and the dequeue port signal (DEQRQ\_SEL) 485 to clear the register array contents.

```

always @(posedge clk or negedge reset) begin
  if (!reset) FIFO2 <= NULLVALUE;
  else if (LOAD_FIFO && STTMP[1])
    FIFO2 <= FIFO1;
  else if (CLR_FIFO && DEQRQ_SEL == FIFO2)
    FIFO2 <= NULLVALUE;
  else
    FIFO2 <= FIFO2;
end

```

#### 7. Blocked Route Request Timer (BRTMR)

The Blocked Route Request Timer 135 (BRTMR) in FIG. 4 implements one timer per PCM. The timer is enabled when a route request is blocked for the particular PCM. The timer is disabled when the blocked route request becomes unblocked. The BRTMR is controlled by the Route Control FSM which not only enables the timer but also indicates which timer to enable. Enabled timers are selected by the port from the incoming route request 104. Disabled timers are selected by the port from the route request selector module 146. The different timers are defined by the ANSI FCPH standard. When a timeout occurs the Route Request Unblock Determination module is signaled 119 to dequeue the blocked request as soon as possible.

#### 8. Route Request Unblock Determination Module (RRUNB)

The Route Request Unblock Determination module 136 (RRUNB) in FIG. 4 determines when and which blocked route request to unblock. The RRUNB reads information from the Blocked Route Request Table 116, the Blocked Route Request Port Register Array 118 the Blocked Route Request Timer 119 and the Route State Table 124. A more detailed view of the RRUNB is shown in FIG. 14, FIG. 15 and FIG. 16.

As shown in FIG. 14 the RRUNB 361 reads information from several internal router modules and determines the most recent and highest priority blocked route request to dequeue from the Blocked Route Request Table. The RRUNB signals the

port to dequeue 371 to both the Blocked Route Request Table and the Router Control FSM. The inputs to the RRUNB include the following information from the Route State Table: Port is currently busy signal 365 and the Port is currently in a class 1 connection signal 366. The inputs to the RRUNB from the Blocked Route Request Table include the blocked route request indication, the destination port in which the blocked route request is waiting for, the block reason (whether waiting for the remote port to become free or both free and disconnected from a Class 1 route), and if the blocked route request is a Class 1 frame.

FIG. 16 shows part of the RRUNB circuit which generates intermediate terms necessary to calculate which blocked route requests to unblock. Each blocked route is waiting for certain conditions to clear from a destination port. The destination port vector 429, 431, 433, 435 is used to select which remote signal to look at 421, 422, 423, 424, to generate the remote status 430, 432, 434, 436. For example if a route request is blocked from port 1 the destination port which port 1 is waiting for is used to select the remote port busy signal. It is also used to select the "remote port is currently in a Class 1 connection signal".

FIG. 15 shows another part of the RRUNB circuit. There are seventeen different DEQx\_FLAGS, only two are shown for brevity, i.e., DEQ0\_FLAG 381 and DEQ16\_FLAG 382. The DEQx\_FLAG signals are generated according to the following circuit:

```
DEQ0_FLAG = Timeout indication for port 0 from RTMR ||
              ((!remote port 0 busy) &&
               (!(block reason == wait for remote port 0 Class 1 connected &&
                 (remote port 0 Class 1 connected))))
```

The timeout indication is generated from the BRTMR module 362 in FIG. 14. The remote port 0 busy 430 and the remote port 0 Class 1 connected signals 434 are generated from the circuit described in FIG. 16. The block reason comes from the BRTBL 369. There is one DEQ0\_FLAG signal for every PCM.

As shown in FIG. 15 each DEQ\_FLAG 381, 382 signal is input into sixteen multiplexers 383, 384, representing the number of potentially blocked route requests. Multiplexer numeral 383 uses the port number in the BRRA register array in position

0, numeral 385, and multiplexer 384 uses the port number in the BRRA register array in position 16 numeral 386. For example if the contents of position 0 in the BRRA register array is port 4 then the DEQ4\_FLAG is select by multiplexer 383 and output to the DEQIND0 signal 387. The DEQIND signals 387, 388 are used as inputs to the  
5 binary encoder block 389. The binary encoder block 389 takes the highest DEQIND signal, DEQ16IND being higher than DEQ0IND and encodes the value to a select 390 which selects the position in the BRRA 392, 393 to dequeue 394. For example if DEQ16IND signal is set then the port number contained in position 16 of the BRRA is output 394 from multiplexor 391.

10 FIG. 15 also describes a similar circuit which accounts for blocked route requests for Class 1 frames. The resulting port derived from this circuit takes precedence to the circuit previously described. This allows priority dequeuing of blocked route requests for Class 1 frames. The circuit uses the DEQx\_FLAGS 387, 388 generated from multiplexors identified by numeral 383 and 384. The  
15 DEQx\_FLAGS are ANDed with the remote port Class 1 connected signals generated in FIG. 16 numerals 434, 436 to form the inputs 396, 397 to the multiplexors identified by numeral 398 and 399. The multiplexors 398, 399 select the destination port contained in the BRRA array 400, 401. The output signals 402, 403 are binary encoded 404 to take the highest input signal to select the position in the BRRA 406, 407 to dequeue 408.  
20

The inputs to multiplexor numeral 395 represent the oldest blocked route request 394 and the oldest blocked route request of a Class 1 frame 408. Multiplexor 395 will give priority to the Class 1 frame port 408 before choosing the oldest non-Class 1 route request 394. The resulting vector 409 is the blocked route request to  
25 dequeue.

This circuit can be used to unblock other types of resources besides Fibre Channel route requests. The circuit is implemented as combinatorial logic and selects the blocked route request within one clock.

## 9. Route Request Selector (RRS)

The Route Request Selector module 137 (RRS) in FIG. 4 functions to select between the incoming route request from the PCRRIM module 108 or the BRTBL 115. The resulting route request is output 110 to the Route Determination module. The RRS is controlled by the Route Control FSM 140.

5           10.   Route Determination Module (RDM)

The Route Determination module 138 (RDM) in FIG. 4 applies rules defined in the ANSI Fibre Channel specifications to calculate how to route the incoming frame. The RDM receives the route request 110 from the RRS 137 along with route context for the source and destination ports 112 from the Route State Table 139. The  
10   RRS outputs the route results 145, 111 to both the Router Control FSM 140 and the PCRSPPM 144. The RDM is implemented in combinatorial logic and applied the route rules in one clock.

FIG. 20 shows the RDM 501 in more detail. The RDM reads the route request from the RRS which includes the source requesting port 503, the destination  
15   port 504, the frame SOF delimiter 505, the EOF received flag 506, the route to port 0 (i.e., fabric controller) flag 507 and the timeout indication 508. The RDM also reads in the route table context for both the source and destination ports 512 and reads in a test enable vector 513. The test enable vector 513 turns off selected route rule checks for more flexibility when the router is implemented in an ASIC. The outputs  
20   from the RDM include the route results vector 509, 510 which indicates whether to route the frame or return an error, the reject/busy action/reason vector 10 which is valid when the RDM detects an error and the route back indication 511 which signals the port that the frame is in error and will routed back to the same port. Finally the updated source and destination port contexts are updated to reflect the RDM actions  
25   514 and wired back to the route state table 502.

FIG. 21 shows the RDM route selection logic in more detail. As mentioned earlier the inputs to the RDM include the route state context for both the source and destination ports 522 and the route request 523. The RDM has prewired rules checks to detect five conditions: discard frame 525, block the route request until the remote  
30   port is not busy 526, return a fabric reject (F\_RJT) frame 527, return a fabric busy

(F\_BSY) frame 528, wait until the frame is completely received 529. If all of the four conditions are not detected then the frame should be routed successfully to the remote port. The conditions mentioned above are derived from the ORing of multiple rules checks. For example the discard frame signal is derived from the ORing of five  
5 discard frame rules checks. An example rules check is shown below.

```
// discard frame if local SOFn1 received and local port is in a class 1
connection
wire DISFRM4 = TEN[2] && DELIM == SOFn1 && SRC_CSTATE ==
Connected;
```

10 The TEN[2] term above selects a bit from the test enable vector. Turning the bit off will disable the above rules check. The rule above will assert the DISFRM4 signal if the incoming frame contains an SOFn1 delimiter and the incoming port is not already in a Class 1 connection.

As shown in FIG. 21 all potential rules check results 531 are encoded and  
15 selected by using the rules checks 525, 526, 527, 528, 529 as the multiplexor selector. The routing result selected is then output 532 to both the Router Control FSM and the PCRSPM. All rules checks are completed within one clock period.

Finally FIG. 22 shows how the preencoded fabric reject 544 and fabric busy responses 548 are selected by the fabric reject 542 and fabric busy 546 rules checks.  
20 The result 551 is output to the PCRSPM module to be included in the route response.

### 11. Route State Table (RST)

FIG. 4 shows the Route State Table (RST) 139. The function of the RST is to keep the current context for each port. The RST interfaces with the Route Determination Module (RDM) 138, the Route Request Unblock Determination Module (RRUNB) 136 and the processor in the Fabric Control module 121. FIG. 20 shows the RST 502 in relation to the RDM 501. The RST is controlled by the Router Control FSM which signals the RST 515 to either output the source and destination context 512 or save the updated source and destination context 514. The RST outputs certain context fields into the RRUNB FIG. 4 numeral 124 to assist in route request unblocking calculation.

The RST contains a context entry for each port. The context entry is shown in FIG. 34. There are two parts to the route context: a static portion which is updated by the processor in the Fabric Control module FIG. 2 numeral 54 and a dynamic portion updated by the RDM module FIG. 4 numeral 138. The processor updates the static portion upon infrequent events such as power up and fabric login. The RDM updates the dynamic portion on a per frame basis. In current commercially available fabrics a processor manages all of the route state table fields, the current embodiment uses a register memory in the RST and the RDM to update the context. The table below lists the context fields.

20	<u>Signal</u>	<u>Description</u>
	Destination Port Connected To	If a route exists this specifies the remote port.
	Class 1 Destination Port	If this port is in a Class 1 connection this field specifies the remote port.
25	Timer State	If this port is waiting for a route and a timer is enabled, this field specifies the timer.
	Class 1 Connection State	This field specifies whether this port is currently in a Class 1 connection.
	Port Busy	This field specifies whether this port is currently routing a frame to a remote port.
	Port State	This field specifies the link state, whether initializing, offline, online, or error.
30	Class Supported	This field specifies the Classes of service supported by this port.
	Loop Port Indication	This field specifies whether this port is a loop port or a point to point port.

Port Speed	This field specifies the link speed for this port.
Intermix Support	This flag specifies support for Intermix for this port.
FLOGI occured	This field specifies whether a FLOGI/ACC exchange occurred.

## 12. Router Statistics Gathering Module (RSG)

5       FIG 4. shows the Router Statistics Gathering Module (RSG) 141. The RSG gathers fabric generated statistics. The RSG is enabled by the Router Control FSM 140 and has as inputs the source and destination ports, the route result and the frame Class 142. The RSG is implemented in hardware because of the requirement of collecting statistics at gigabit rates.

## 10       13. Router Control FSM (RCFSM)

FIG. 4 shows the Router Control FSM (RCFSM) 140. The RCFSM controls the entire router through control signals to the internal router modules 147. The RCFSM state diagram is shown in FIG. 18.

15       The RCFSM is triggered from idle by one of three events: a processor request to read or write a router data structure 470, a blocked route request becoming unblocked 471 or an incoming route request received from a port control module signal 472. The three events are prioritized in case of multiple simultaneous events. The priorities from high to low include: 1) processor request, 2) a blocked route request becoming unblocked and 3) an incoming route request. When a processor updates any of the router fields the router must be in a quiescent state, i.e., not updating any data structure. When a processor requests access to a router data structure the processor signals the RCFSM by asserting the BLKCTLREQ signal. If in idle the RCFSM enters the RTBLKED state 452 and waits until the processor has finished its access. While in the RTBLKED state the RCFSM signals it is in this state by asserting the BLKCTLACK signal. The router processor interface logic will hold off the processor access via a WAIT signal until the BLKCTLACK signal is enabled.

25       The remaining RCFSM diagram states and description is discussed below. Refer to FIG. 18 for the state diagram and to FIG. 4 for the module description.

	<u>State</u>	<u>Description</u>
	DEQROUTE 467	Program RRS 137 to use the newly unblocked route request as an input 115
	CLR_FIFO 468	Signal the BRTBL 133 to remove the blocked route
	DECODERRSP 455	Wait one clock for the RDM 138 to apply routing rules checks to the route request 110
5	RTOK 456	The RDM 138 has determined the route is ok. Signal the RST 139 to update the route table, signal the RSG 141 to collect statistics for this route and select the destination port from the ADM 131 results.
	RTBSY 459	The RDM 138 has determined to return a fabric busy (F_BSY) frame to the sending port. Signal the RST 139 to update the route table, signal the RSG 141 to collect statistics and assign the destination port from the source port (i.e., route F_BSY back to the same port).
	RTRJT 460	The RDM 138 has determined to return a fabric reject (F_RJT) frame to the sending port. Signal the RST 139 to update the route table, signal the RSG 141 to collect statistics and assign the destination port from the source port (i.e., route F_RJT back to the same port).
	RTDISCARD 461	The RDM 138 has determined that the port control module should discard the frame. Signal the RSG 141 to collect statistics.
	RTWAIT_EOF 462	The RDM 138 has determined that the port control module should wait until the entire frame is received before resubmitting the route request.
10	RTBLK 463	The RDM 138 has determined to block the route request. The BRTBL 133 and the BRRA 134 are signaled to save the route request and save the port requesting the route.
	PGMSW 457	Program the switch core 123 to make a path from the source to the destination port.
	RTNRSP 458	Signal the PCRRSPM 144 to return a route request complete indication.
	LDRTSTATE 464	Signal the RST 139 to update its context and signal the BRTMR 104 to enable a blocked route request timer.
	LD_RT 453	Signal the RRS 137 to read the route request 108 that was just read from the PCRRIM 130.

SOFOR EOF 454	Signal the PCRRIM 130 to fetch another route request since the current request is registered in the RRS 137 module. Load the route results from the RDM 138 into the PCRRSPM 144 (in case delimiter is an EOF). Go to the DECODERRSP 455 state if the delimiter in the route request is an SOF otherwise go to the EOFDELIM 465 state.
EOFDELIM 465	Signal the RRS 137 to use the destination port from the route context in the RST 139.
DISTIMER 466	Signal the switch core to disconnect the path from the specified source port to the destination port, signal the RST 139 to update the route table context to reflect the disconnected path and signal the PCRRSPM 144 to return a route request complete indication.

#### E. Port Control

5           FIG. 2 shows the Port Control (PC) locations 51, 70, 74, 75, within the fabric block diagram. Preferably, there is one PC per port or link. The PC interfaces with the fabric attached device through either copper or fiber media 56, 77, 78. The PC interfaces to the switch core through transmit 58 and receive 57 data buses and control signals. The PC interfaces to the router through route request 59, 61, 66, 72 and route response 60, 62, 67, 73 buses and control signals. Finally the PC interfaces to the Fabric Control module through a processor interface bus 65.

10           FIG. 5 shows the Port Control in more detail. Frames are received from the fiber or copper link 151 and enter the Endec 153. The Endec implements the 8B/10B encoding/decoding, the loop port state machine and fabric/point-to-point state machine functions and outputs thirty two bit data words with two bits of parity and tag information to the receive FIFO 155. The PC contains a module which guards against a receive FIFO overrun 154 condition. Once the receive FIFO 155 starts filling, the Port Control Module (PCM) 156 reads the frame header, requests a route from the router 163, 164 and forwards the frame to the switch core 161, 162. The PCM is configurable by the processor 170 in the Fabric Control module. The Port Control also receives frames from the switch core 165, 166 to be transmitted by the Endec 153.

### Port Control Module (PCM)

FIG. 10 shows the Port Control Module (PCM) in more detail. The PCM is responsible for reading a portion of the received header from the input FIFO 250, building a route request for the router 262, 263, 264, 260, receiving the route response from the router 265, 266, 261 and either forwarding the frame to the switch core 249 or building a fabric reject (F\_RJT) or fabric busy (F\_BSY) frame and forwarding those to the switch core. The PCM also performs miscellaneous functions such as receive frame validation against parity errors, short frames, frames too large, tag errors and other checks.

The PCM is composed of the following four modules:

- (1) Port Control FIFO Module (PCFIFO) 247
- (2) Port Control to Router I/F Module (PCRTIF) 234
- (3) Port Control Main Control FSM (PCFSM) 232
- (4) Port Control Configuration/Counter Module (PCCFG) 233

#### 1. Port Control FIFO module (PCFIFO)

FIG. 10 shows the Port Control FIFO module (PCFIFO) 247. The PCFIFO buffers several words of the incoming frame with internal registers. The registers include four general input registers (fifo\_reg0 237, fifo\_reg1 238, fifo\_reg2 239, fifo\_reg3 240), five special input registers (sof\_reg 241, rctldid\_reg 242, type\_reg 243, param\_reg 244, eof\_reg 245) and a main input and output register (EDATA\_OUTR 236 and SW\_DATAIN 246). The input register (EDATA\_OUTR) gates the data in from the input FIFO 250 by asserting the FIFOREQ\_ signal. The output register sends the data to the switch core by asserting the SWACK\_ signal 249. The general and special input registers are loaded from the EDATA\_OUTR register. The general and special registers also are connected to a multiplexor which feeds the SW\_DATAIN register 246. The special registers allow the PCFIFO to build fabric reject (F\_RJT) and fabric busy (F\_BSY) frames and to insert special EOF delimiters when the route response 261 specifies to do so.

The received destination address (D\_ID) along with the SOF delimiter is wired to the PCRTIF module 254 to build the route request 260. Finally the PCFIFO is controlled by the PCFSM 232.

5 The PCFIFO module performs certain frame validations. These validations include parity and tag field checking and regeneration, CRC, invalid transmit word and link down while receiving frame validations. When the frame validations fail the PCFIFO automatically inserts the appropriate EOF delimiter 251, either an EOFa, EOFni or EOFdti.

10 The PCFIFO will build a fabric frame reject (F\_RJT) when the route response from the router specifies to do so 261. The PCFIFO builds the fabric reject by changing certain fields in the frame header 241, 242, 244. Since the entire header is not yet in the PCFIFO internal registers a counter is implemented to indicate when to insert the modified header fields. The frame fields which are modified include the R\_CTL field 242, the parameter field 244 and potentially the EOF delimiter 245. In  
15 addition if there was a payload associated with the frame it is discarded.

The PCFIFO will also build a fabric busy (F\_BSY) frame when the route response from the router response specifies to do so 261. The PCFIFO modifies the R\_CTL field 242, the type field 243 and potentially the EOF delimiter 245. As in the F\_RJT frame modification the payload for the F\_BSY frame is discarded.

## 20 2. Port Control Main Control Module (PCFSM)

FIG. 10 shows the Port Control Main Control Module (PCFSM) module 232 (PCM). The PCFSM controls the other modules which compose the PCM 252, 258, 272. The PCFSM is triggered by a frame being received from the input FIFO. FIG. 11 shows the PCFSM state diagram and is described in detail below.

25	<u>State</u>	<u>Description</u>
	IDLE 301	Wait until the first three words of a frame are received from the input FIFO. This is the first state after a system reset.
	CLRSOF 302	A frame has been received. Reset the EOF register and start the route request signal if the frame is not a short frame.

	ROUTEFRM 303	In this state the PCFSM signals the PCRTIF to send a route request (RREQ) to the router. The PCFSM will loop in this state until a route response (RRACK) is received back from the router.
	XMTFRM 304	Transmit the frame through the Port Control from the input receive FIFO to the switch core.
	RTNRJTBSY 308	The router has determined that a fabric reject (F_RJT) or fabric busy (F_BSY) frame should be returned. The SOF delimiter is modified along with the R_CTL field.
	WAITEOF 306	Wait until an EOF is received. The Port Control usually implements cut through routing, i.e., when a frame is received it is forwarded to the remote before the end of frame is received. Certain conditions dictate that the frame should be received in its entirety before being forwarded. An example condition includes the remote port speed is lower than the source port.
5	DISCRT 305	Signal the PCRTIF to send a route disconnect request (RREQ) and loop in this state until a route disconnected response (RRACK) signal is received.
	UPDATE_CDT 306	This one clock state is entered into after transmitting or discarding a frame. If a Class 2 or Class 3 frame was operated on the Endec CREDIT_ signal is pulsed. The EOF register (RESET_EOF) is cleared, the frame counter is cleared and the EOF in received FIFO counter is decremented.
	WAITEOF1 309	Wait until an EOF is received from the Endec due to a F_RJT/F_BSY frame being returned. An EOF must be received so as to not cause a transmitter underrun at the remote Endec.
10	XMT_FRJTBSY 10	Wait until an EOF is transmitted which signals that the F_RJT or F_BSY EOF was transmitted. While in the XMT_FRJTBSY state assert either the xmt_frjt or xmt_fbsy signal to the PCFIFO module to specify which frame to transmit.

### 3. Port Control Configuration/Counter Module (PCCFG)

FIG. 10 shows the Port Control Configuration/Counter (PCCFG) module 233. The PCCFG maintains counters and provides the processor interface 271 to the Port Control Module. The PCCFG contains an EOF received counter 267, a current frame count register 268 and a port control configuration register 269. The EOF received counter keeps track of the number of full frames received by the Endec contained in

the receive frame FIFO. The current frame count register monitors the current number of words received on a per frame basis. This counter is used to detect short and long frames. Finally the port control configuration register contains miscellaneous information/configuration information used by the Port Control module.

The port control configuration register fields are described below.

	<u>Field</u>	<u>Bit Location</u>	<u>Description</u>
	Max Frame Size	9:0	Indicates the maximum receive frame size in words.
	LISM Mode	10	The Port is currently going through loop initialization indication
10	Clear Interrupt	11	Clear the bad parity notification interrupt.
	Pulse CDT_line	12	Pulse the Endec credit line.
	Clear Interrupt	13	Clear interrupt latch
	Enable Remote Port Routing	14	Enable preemptive remote port routing.
15	This Port Number	19:16	
	EOF Counter	26:24	Counter value for the number of EOF delimiters received from the Endec.
	Frame Discarded	27	Frame was discarded by the Port Control.
	Frame Too Short Detected	28	A frame which was less than eight words in length was received.
20	Frame Too Big Received	29	A frame which was greater than the specified maximum frame size (bits 9 to 0) was received.
	Tag Error occurred	30	A tag error was detected (i.e., a tag of either 00 or 11).
25	Parity Error occurred	31	Clear parity interrupt indication register.

#### 4. Port Control to Router Interface Module (PCRTIF)

FIG. 10 shows the Port Control to Router Interface Module (PCRTIF) 234. The PCRTIF builds route requests for the router 260, signals the router that a valid request is present 262, waits for a router response valid signal (RTPCREQ) 263 and receives the router response 261. The PCRTIF builds the route request from the D\_ID field, the SOF delimiter and some miscellaneous signals from both the PCFIFO 254 and the PCCFG 273 modules. The route request is transmitted over a shared

command channel bus 264 to the router. This command channel bus is shared by all the PCMs. The route response is received over a different shared response channel bus (RT\_DATA) 266 which is also shared by all the PCMs. By implementing different buses or channels for the route request and route response the router can  
5 simulataneously read route requests along with returning route responses.

#### FIFO Overrun Prevention Logic (FOPL)

FIG. 5 shows the FIFO Overrun Prevention Logic (FOPL) 154 within the Port Control area. The purpose of the FOPL is to handle the case where the FIFO 155 is full and frames are received by the Endec 153. Since the frame arrival rate is  
10 extremely fast at gigabit link data rates, the FOPL must act in real time. An additional situation the FOPL must handle is when the frame arrives and is being routed to the remote port and the back end of the frame overruns the FIFO. Still another situation is where multiple frames overrun the FIFO. The FOPL operates on the TAG bits 154 not the data bits 171. The Endec takes gigabit serial transmission  
15 from the link side, decodes the transmission and outputs thirty two bit words to the port control FIFO. Along with the thirty two bit words are a two bit tag field and a two bit parity field. The tag and parity field additions are a common interface characteristics. Tag bits are bits attached to the thirty two bit words to indicated delimiters such as the SOF or EOF. When the FIFO is full and a frame is received  
20 from the Endec the FOPL sets the tag bits to an illegal value. When the FIFO enters the not full condition the next word will contain the illegal tag bits. The illegal tag bits will signal the Port Control modue to abort the frame with the appropriate EOF delimiter.

FIG. 8 shows the FOPL in more detail. The FOPL 201 interfaces with the  
25 Endec tag bits 202, the Endec receive frame DMA request signal 203, and the Endec receive frame DMA acknowledgement 204 signal. The FOPL interfaces with the FIFO by supplying the tag bits and through the FIFONOTEMPTY 206 signal. During normal operation the FOPL will set the FIFO tag bits 205 to the value of the Endec tag bits 202. When the FIFO is full, i.e., when the FIFONOTEMPTY signal  
30 206 is deasserted, the FOPL will output an illegal value for the tag bits 205 going to

the FIFO. If the overflow word is the last word to be received the FOPL will wait until the FIFONOTEMPTY signal 206 is asserted and then output a word with bad tag bits by asserting the FIFOWRITE 207 signal. This last scenario handles the case where the last word received overflows the FIFO and there are no other words to receive.

#### Processor/Data Arbitration Logic (PDAL)

FIG. 5 shows the Processor/Data Arbitration Logic (PDAL) 157 within the Port Control area. Since the Endec 153 multiplexes the transmit bus with the internal register configuration bus, logic is needed to arbitrate between processor accesses 168 and frames being transmitted from the switch core 166. This logic must manage processor accesses to the Endec which are slower than transmit data word dma's. In other words if a frame is currently being transmitted, processor accesses to the Endec must be held off until either the frame transmission is complete or the internal Endec transmit FIFO is full, allowing enough time for a processor access before a transmitter underrun occurs.

The PDAL acts as the arbitrator between processor accesses and transmit data to the Endec. The PDAL accomplishes this by keeping track of when the switch core is transmitting frames to the Endec and inserting processor accesses between frames or when the Endec's internal transmit FIFO is full. FIG. 9 shows the PDAL in more detail. The PDAL interfaces to the Endec through the Endec transmit frame DMA request 209 signal, the chip select 208 and the wait 207 signals. The PDAL interfaces with the switch core through the transmit frame dma request signal 212. The PDAL interfaces with a bus transceiver 225 through an enable signal 216. The PDAL interfaces with the processor from the Fabric Control module through the chip select 214, wait 215 and write 222 signals. Finally the PDAL interfaces to the Router Module through the route busy 226 signal. The processor will only access the Endec transmit/configuration bus 224 when the wait signal 215 is deasserted. The PDAL uses two conditions to create the processor wait signal. The first condition is that there are no frames being transmitted to the Endec. This condition is indicated by the route busy signal 226 from the router being deasserted. The second condition is the

transmit frame dma request signal 209 deasserted, indicating that the internal Endec transmit FIFO is full. The second condition creates enough time for a processor access to the Endec internal registers before the Endec's internal transmit FIFO empties.

5     Port Control Hub Module

FIG. 29 shows the Port Control Hub Module (PCHM). The PCHM extends the functionality of the Port Control Module by adding several Fibre Channel Arbitrated Loop Hub ports. This has the affect of leveraging a single switch port over multiple attached devices 705. All attached devices 705 are logically on a single loop connected to the switch through an internal Endec 700. The internal Endec is connected on the loop by both a transmit 701 and receive 702 serdes modules. The output of the serdes module is a gigabit serial stream of data. The loop is repeated by commercially available 1.0625 Gbit/sec Channel Repeater/Hub Circuits 703 such as Vitesse's VSC7120. (See, e.g., Vitesse Semiconductor Corporation "1996 Communications Products Data Book"). The repeater/hub circuits contain a monolithic Clock Recovery Unit (CRU), a digital Signal Detect Unit (SDU) and a Port Bypass Circuit (PBC). The repeater/hub circuits allow devices to attach and detach without interrupting the loop. The repeater/hub circuits are connected to a Gigabit Interface Converter (GBIC) module 704 which supports either copper or fiber media via a plug in module. All repeater/hub circuits are controlled by the fabric control processor through a register 705. This allows the fabric control module to monitor the state of each port and integrate the status with the general switch network management.

25     The integral hub provides many advantages over standalone hubs. These advantages include:

Leveraging the redundant power supplies and fans usually resident in the fabric

Segmenting loops to allow for increased performance per loop and greater immunity from loop failure

30     Allowing for hot pluggable hub boards

Leveraging the switches SNMP network management capability for greater control and monitoring of the loop.

F. Switch Core

FIG. 2 and 6 shows the Switch Core. The switch core implements a nonblocking NxN matrix switch. The input to the switch core comes from the individual Port Control modules FIG. 2 numerals 57, 69 and FIG. 9 183, 186. The output from the switch core is wired to the Endec FIG. 2 numeral 58, FIG. 9 numeral 220 and the Brouter Module FIG. 2 numeral 76. The switch core is paths are setup and torn down by the router FIG. 2 numeral 63.

G. Brouter Module

FIG. 2 numeral 55 and FIG. 7 show the Brouter Module. The Brouter Module receives frames from the switch core 76 and transmits frames to the internal Port Control module 70. The Brouter Module is responsible for converting Fibre Channel frames to frames of the connected network 68. The Brouter Module looks to the rest of the fabric like a Port Control module. The Brouter module sends and receives frames which adhere to the Fibre Channel protocol. The frames are converted within the Brouter module to other network frames such as Ethernet, Fast Ethernet, or Gigabit Ethernet and are transmitted out to the network connection 68.

Although the foregoing invention has been described in some detail by way of illustration and example for purposes of clarity and understanding, it may be readily apparent to those of ordinary skill in the art in light of the teachings of this invention that certain changes and modifications may be made thereto without departing from the spirit or scope of the appended claims.

H. Other Documents

ANSI X3.230-1994, "Fibre Channel Physical and Signaling Interface (FC-PH)".

ANSI X3.297-1996, "Fibre Channel Physical and Signaling Interface (FC-PH-2)".

ANSI X3.303-1996, "Fibre Channel Physical and Signaling Interface (FC-PH-3)".

ANSI X3.272-1996, "Fibre Channel Arbitrated Loop (FC-AL)".

ANSI X3T11 Project # 1133-D, "Fibre Channel Arbitrated Loop 2 (FC-AL2)".

ANSI X3T11/95-41, "Fibre Channel Fabric Generic Requirements (FC-FG), Rev 3.2"

ANSI X3T11 Project 1134-D "(FC-GS2)".

ANSI X3T11 Project 959-D "Fibre Channel Switch Topology (FC-SW)".

ANSI X3T11 Project 1235-DT, "Fibre Channel Fabric Loop Attachment (FC-FLA) Rev 2.2"

FCA "N\_Port to F\_Port Interoperability Profile, Rev 1.0"

## I Claim:

1. A fibre channel switching fabric for connecting multiple attached devices comprising:
  - multiple port control modules, the port control modules being adapted  
5 for communication with the attached devices, the port control module functioning to build a route request and read a route response,  
a router module, the router module being connected to the port control modules by a route request connection and by a separate route response connection, and  
10 a switch core, the switch core being connected to the port control modules.
2. The fibre channel switching fabric of claim 1 for connecting multiple attached devices further including a fabric control module connected to the router module and port control modules.
- 15 3. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein there is one port control module for each attached device.
4. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein at least one port control module is attached to a arbitrated loop having multiple attached devices.
- 20 5. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the port control module further serves to modify frames.
6. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the port control module modifies frames to fabric frame busy (F\_BSY).

7. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the port control module modifies frames to fabric frame reject (F\_RJT).

8. The fibre channel switching fabric of claim 1 wherein the port control  
5 module further functions to discard frames.

9. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the port control module performs frame validation.

10. The fibre channel switching fabric of claim 9 for connecting multiple attached devices wherein the frame validation includes parity error validation.

10 11. The fibre channel switching fabric of claim 9 for connecting multiple attached devices wherein the frame validation includes invalid transmit word correction.

12. The fibre channel switching fabric of claim 9 for connecting multiple  
15 attached devices wherein the frame validation detects frame size error.

13. The fibre channel switching fabric of claim 9 for connecting multiple attached devices wherein the port control module further performs frame connection.

14. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the fabric is connected in a direct fabric attached topology.

20 15. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the fabric is connected in an arbitrated loop attached topology.

16. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the attached devices include fibre channel compliant devices selected from the group comprising: a mainframe, a workstation, a personal computer, a storage device and a disk array.

5 17. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the attached devices include a second fabric.

18. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the switch core comprises a full crossbar.

19. The fibre channel switching fabric of claim 1 for connecting multiple  
10 attached devices further including a bridge module.

20. The fibre channel switching fabric of claim 1 for connecting multiple attached devices further including a hub module.

21. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the attached devices are connected to the fabric by a serial  
15 link.

22. The fibre channel switching fabric of claim 21 for connecting multiple attached devices wherein the link is a copper connection.

23. The fibre channel switching fabric of claim 21 for connecting multiple attached devices wherein the link is a fiber optic connection.

20 24. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the fabric receives fibre channel frames of at least one gigahertz.

25. The fibre channel switching fabric of claim 1 for connecting multiple attached devices which supports Class 1 service.

26. The fibre channel switching fabric of claim 1 for connecting multiple attached devices which supports Class 2 service.

5 27. The fibre channel switching fabric of claim 1 for connecting multiple attached devices which supports Class 3 service.

28. The fibre channel switching fabric of claim 1 for connecting multiple attached devices which supports each of Class 1, Class 2 and Class 3 service.

29. The fibre channel switching fabric of claim 28 for connecting multiple  
10 attached devices which further supports intermix service.

30. A method for servicing route requests from multiple attached devices where the routing is subject to blocked and unblocked conditions, the method comprising the steps of:

servicing a route request which is not blocked, and  
15 saving a blocked route request in hardware and servicing that request if the route changes from a blocked to an unblocked condition prior to the expiration of a specified time period.

31. The method of claim 30 wherein the saved route request includes sufficient information to regenerate the route request once the blocked condition is  
20 cleared.

32. The method of claim 31 wherein the saved information regarding the blocked route request includes the requesting port control module port.

33. The method of claim 31 wherein the saved information regarding the blocked route request includes a matched destination port control module port.

34. The method of claim 31 wherein the saved information regarding the blocked route request contains the blocking condition.

5        35. The method of claim 31 wherein the saved information regarding the blocked route request includes the indication of an end of frame delimiter being received by the requesting port control module port.

36. The method of claim 31 wherein the saved information regarding the blocked route request includes a delimiter in the incoming frame.

10       37. The method of claim 31 wherein the saved information regarding the blocked route request includes whether there was an address match.

38. The method of claim 31 wherein the saved information regarding the blocked route request includes whether to route to the fabric port control module.

15       39. The method of claim 31 wherein the saved information regarding the blocked route request includes whether a fabric reject frame (F\_RJT) is to be generated.

40. The method of claim 31 wherein the saved information regarding the blocked route request includes whether a fabric busy frame (F\_BSY) is to be generated.

20       41. A fibre channel fabric for connecting multiple attached devices supporting connection based service and connectionless based service between attached devices, comprising:

multiple port control modules, the port control module being adapted for connection to an attached device,

a router, the router being in communication with the port control modules to receive route requests and to generate route responses and to provide the route responses to the port control modules, the port control modules being connected to the router by separate route request connections and route response connections, and

a single switch core for support of connection based service between attached devices and connectionless based service between attached devices.

42. The fibre channel fabric of claim 41 for connecting multiple attached devices further including a fabric control, the fabric control in communication with the port control modules.

43. The fibre channel fabric for connecting multiple attached devices of claim 41 wherein the single switch core is a non-blocking switch core.

44. The fibre channel fabric for connecting multiple attached devices of claim 41 wherein the dedicated connection is maintained in the switch core until a removal request is received.

45. A fibre channel fabric for connecting multiple attached devices supporting connection based service and connectionless based service between attached devices, comprising:

multiple port control modules, the port control module being adapted for connection to an attached device,

a router, the router being in communication with the port control modules to receive route requests and to generate route responses and to provide the route responses to the port control modules, the router constructing a route in two microseconds or less, and

a single switch core for support of connection bases service between attached devices and connectionless based service between attached devices.

46. A fibre channel fabric for connecting multiple attached devices supporting connection based service and connectionless based service between attached devices, comprising:

5 multiple port control modules, the port control module being adapted for connection to an attached device,

a router, the router being in communication with the port control modules to receive route requests and to generate route responses and to provide the route responses to the port control modules, the router including multiple state machines which result in pipelined operation for handling route requests and route responses, and

10 a single switch core for support of connection bases service between attached devices and connectionless based service between attached devices.

47. A fibre channel switching fabric for connecting multiple attached devices comprising:

15 multiple port control modules, the port control modules including a connection for communication with attached devices, a route request generator, and a route request response receiver,

a router, the router including an input for receiving the output of the route request generator of the port control modules, an output for sending a route request response to the route request response receiver in the port control module, a hardware finite state machine to receive the route request, and a hardware finite state machine to provide the route response, the router further including a route determination system which determines a route within a single clock cycle of the system, and

20 a switch for selective interconnect of the port control modules.

48. The fibre channel switching fabric of claim 47 for connecting multiple attached devices wherein the router control includes a hardware finite state machine.

49. The fibre channel switching fabric of claim 47 for connecting multiple attached devices wherein the single clock cycle is 30 nanoseconds or less.

50. An improved port control module for use in a fibre channel switching fabric comprising:

- 5           an input/output port for connection to a link,  
          an encoder/decoder in communication with the input/output port, and  
          a buffer,  
          the improvement comprising the inclusion of buffer overrun prevention logic between the encoder/decoder and the buffer.

10          51. The improved port control module for use in a fibre channel switching fabric of claim 50 wherein the buffer is a first-in, first-out buffer.

52. The improved port control module for use in a fibre channel switching fabric of claim 50 where the buffer overrun prevention logic sets tag bits to a unique value indicative of an overrun conditions.

15          53. A method for control of an input buffer, where the input buffer is adapted to receive a stream of data at a rate which is not subject to control by the buffer, comprising the steps of:

- receiving the data,  
          placing the data in the buffer,  
20          monitoring for an overflow condition,  
          and if an overflow condition is detected, including a detectable signal in association with the data, and  
          providing the data from the buffer and the detectable signal to subsequent devices.

25          54. The method of claim 53 for control of an input buffer, the detectable condition comprising tag bits.

55. The method of claim 54 for control of an input buffer wherein the tag bits are set to a unique condition.

56. A fibre channel switching fabric for connecting multiple attached devices, comprising:

5 multiple port control modules, the modules being adapted for communication over links to the attached devices,

a router connected to the port control modules, the router including:

a port control route request state machine,

a port control route response state machine, and

10 a route determination module,

the port control route request state machine, the route determination module and the port control route response state machine connected in a serial manner for pipeline operation, and a switch connected to the port control modules and the router.

15 57. The fibre channel switching fabric of claim 56 for connecting multiple attached devices further including a fabric control system connected to the port control modules and router.

58. The fibre channel switching fabric of claim 56 for connecting multiple attached devices further including a router control state machine.

20 59. The fibre channel switching fabric of claim 56 for connecting multiple attached devices wherein the port control route request state machine includes a round-robin arbitration selection unit which is connected to the port control modules.

60. The fibre channel switching fabric of claim 59 for connecting multiple attached devices wherein each port control module is separately connected to the  
25 round-robin arbitration selection unit.

61. The fibre channel switching fabric of claim 60 for connecting multiple attached devices wherein the port control modules are connected to the port control route request state machine by a shared route request data channel and separate route request connections.

5        62. The fibre channel switching fabric of claim 61 for connecting multiple attached devices wherein the selection unit and the route request state machine provide a signal to the port control module which has been selected.

63. A communication system for connecting multiple attached devices comprising:

10                multiple port control modules,  
                  a router connected to the port control modules,  
                  a switch core connected to the router and the port control modules, the router providing selective interconnection between the port control modules, and

15                an arbitrated loop adapted to connect to multiple attached devices, the arbitrated loop being connected to a port control module.

64. A method for handling blocked route requests in a communications system, where a route request includes at least a destination address, a source address and priority information, comprising the steps of:

20                receiving the route request,  
                  determining if the route can be completed,  
                  if the route cannot be completed, storing the route request,  
                  determining when to effectuate the route indicated by the route request and based upon the priority and state information, and

25                completing the route when indicated by the time condition and the priority condition.

65. The method for handling blocked route requests in a communication system of claim 64 wherein the priority information is from the group comprising: Class 1, Class 2 and Class 3 service.




Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6







Figure 7



**Figure 8**



**Figure 9**



**Figure 10**




Figure 11




Figure 12




Figure 13




Figure 14

7/15




Figure 15




Figure 16




Figure 17




Figure 18

10/15




Figure 19




Figure 20




Figure 21




Figure 22




Figure 23




Figure 24




Figure 25




Figure 26




Figure 27




Figure 28




Figure 29




Figure 30




Figure 31




Figure 32




Figure 33




Figure 34

# INTERNATIONAL SEARCH REPORT

Inte Jonal Application No

PCT/US 98/02048

A. CLASSIFICATION OF SUBJECT MATTER  
IPC 6 H04L12/44

According to International Patent Classification(IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 H04L

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	ANUJAN VARMA ET AL: "USING CAMP-ON TO IMPROVE TE PERFORMANCE OF A FIBRE CHANNEL SWITCH"	1,16,18,21,23-28,41-44
Y	PROCEEDINGS OF THE CONFERENCE ON LOCAL COMPUTER NETWORKS, 1 January 1993, pages 247-255, XP000562898 see the whole document	4-15,22,29,46,50,51,53-58,6330-40,64,65
A	---	---

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

\* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"Z" document member of the same patent family

Date of the actual completion of the international search

22 June 1998

Date of mailing of the international search report

20/07/1998

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,  
Fax: (+31-70) 340-3016

Authorized officer

Perez Perez, J

# INTERNATIONAL SEARCH REPORT

Int'l. Application No  
PCT/US 98/02048

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT		
Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	KUMAR MALAVALLI: "HIGH SPEED FIBRE CHANNEL SWITCHING FABRIC SERVICES" PROCEEDINGS OF THE SPIE, vol. 1577, 4 September 1991, pages 216-226, XP000562869 see page 221, line 17 - page 222, line 15 see page 226, line 1 - line 5 see figure 9	1-3, 14-17, 25-28,41
A	-----	60-62,65
Y	US 5 598 541 A (MALLADI SRINIVASA R) 28 January 1997  see figure 10 see column 5, line 19 - column 9, line 47	4-15,22, 29,50, 51,63
A	see column 14, line 56 - column 15, line 49 -----	46
Y	US 4,958 341 A (HEMMADY JAYANT G ET AL) 18 September 1990	46,56-58
A	see column 9, line 58 - column 10, line 3 see column 11, line 56 - column 12, line 7 -----	45,47,64
Y	PLATT A ET AL: "TRAFFIC MANAGEMENT IN FRAME RELAY NETWORKS" COMPUTER NETWORKS AND ISDN SYSTEMS, vol. 23, no. 4, 1 January 1992, pages 305-316, XP000246524 see paragraph 7.1 see paragraph 7.5 -----	53-55
A	EP 0 709 987 A (HEWLETT PACKARD CO) 1 May 1996 see column 5, line 18 - column 6, line 7 -----	1,46, 56-62
A	G.R. STEPHENS ET AL.: "Fibre Channel. The basics." 1995, ANCOT CORPORATION, USA XP002068389 see page 9.1 - page 10.17 -----	1-65

# INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 98/02048

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 5598541	A	28-01-1997	NONE	
US 4958341	A	18-09-1990	AU 599860 B	26-07-1990
			AU 3233789 A	12-10-1989
			CA 1312133 A	29-12-1992
			DE 68926795 D	14-08-1996
			DE 68926795 T	09-01-1997
			EP 0335562 A	04-10-1989
			ES 2088891 T	01-10-1996
			HK 179396 A	04-10-1996
			JP 2013042 A	17-01-1990
			JP 2112391 C	21-11-1996
			JP 8021950 B	04-03-1996
			US 4872160 A	03-10-1989
EP 0709987	A	01-05-1996	US 5490007 A	06-02-1996
			CA 2154716 A	01-05-1996
			JP 8256180 A	01-10-1996

(51) International Patent Classification <sup>6</sup> : H04L 12/44		A1	(11) International Publication Number: WO 98/36537
			(43) International Publication Date: 20 August 1998 (20.08.98)
(21) International Application Number: PCT/US98/02048		(81) Designated States: CA, JP, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(22) International Filing Date: 4 February 1998 (04.02.98)		Published With international search report. With amended claims.	
(30) Priority Data: 08/801,471 18 February 1997 (18.02.97) US		Date of publication of the amended claims: 23 December 1998 (23.12.98)	
(71) Applicant: ARCXEL TECHNOLOGIES, INC. [US/US]; Suite 100, 15245 Alton Parkway, Irvine, CA 92618-2307 (US).			
(72) Inventor: BERMAN, Stuart, B.; 2010 Vista Caudal, Newport Beach, CA 92660 (US).			
(74) Agents: MURPHY, David, B. et al.; Lyon & Lyon LLP, Suite 4700, 633 West Fifth Street, Los Angeles, CA 90071-2066 (US).			

[illegible]

The Fibre Channel standard was created by the American National Standard for Information Systems (ANSI) X3T11 task group to define a serial I/O channel for interconnecting a number of heterogeneous peripheral devices to computer systems as well as interconnecting the computer systems themselves through optical fibre and copper media at gigabit speeds (i.e., one billion bits per second). Multiple protocols such as SCSI (Small Computer Serial Interface), IP (Internet Protocol), HIPPI, ATM (Asynchronous Transfer Mode) among others can concurrently utilize the same media when mapped over Fibre Channel. A Fibre Channel Fabric is an entity which transmits Fibre Channel frames between connected Node Ports. The Fibre Channel fabric routes the frames based on the destination address as well as other information embedded in the Fibre Channel frame header. Node Ports are attached to the Fibre Channel Fabric through links.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav	TM	Turkmenistan
BF	Burkina Faso	GR	Greece		Republic of Macedonia	TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's	NZ	New Zealand		
CM	Cameroon		Republic of Korea	PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

## AMENDED CLAIMS

[received by the International Bureau on 18 September 1998 (18.09.98);  
original claims 1 and 56 amended; new claims 66 and 67 added;  
remaining claims unchanged (3 pages)]

1. A fibre channel switching fabric for connecting multiple attached devices comprising:

multiple port control modules, the port control modules being adapted  
5 for communication with the attached devices, the port control module functioning to build a route request and read a route response,

a hardware router module, the router module being connected to the port control modules by a route request connection and by a separate route response connection, and

10 a switch core, the switch core being connected to the port control modules.

2. The fibre channel switching fabric of claim 1 for connecting multiple attached devices further including a fabric control module connected to the router  
15 module and port control modules.

3. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein there is one port control module for each attached device.

20 4. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein at least one port control module is attached to a arbitrated loop having multiple attached devices.

5. The fibre channel switching fabric of claim 1 for connecting multiple  
25 attached devices wherein the port control module further serves to modify frames.

6. The fibre channel switching fabric of claim 1 for connecting multiple attached devices wherein the port control module modifies frames to fabric frame busy (F\_BSY).

55. The method of claim 54 for control of an input buffer wherein the tag bits are set to a unique condition.

56. A fibre channel switching fabric for connecting multiple attached devices, comprising:

5 multiple port control modules, the modules being adapted for communication over links to the attached devices,  
a hardware router connected to the port control modules, the router including:

10 a port control route request state machine,  
a port control route response state machine, and  
a route determination module,  
the port control route request state machine, the route determination module and the port control route response state machine connected in a serial manner for pipeline operation, and  
a switch connected to the port control modules and the router.

15 57. The fibre channel switching fabric of claim 56 for connecting multiple attached devices further including a fabric control system connected to the port control modules and router.

58. The fibre channel switching fabric of claim 56 for connecting multiple attached devices further including a router control state machine.

20 59. The fibre channel switching fabric of claim 56 for connecting multiple attached devices wherein the port control route request state machine includes a round-robin arbitration selection unit which is connected to the port control modules.

25 60. The fibre channel switching fabric of claim 59 for connecting multiple attached devices wherein each port control module is separately connected to the round-robin arbitration selection unit.

65. The method for handling blocked route requests in a communication system of claim 64 wherein the priority information is from the group comprising: Class 1, Class 2 and Class 3 service.

5 66. The fibre channel switching fabric of claim 56 for connecting multiple attached devices wherein the route determination module is implemented in hardware.

67. A fibre channel switching fabric for connecting multiple attached devices comprising:

multiple port control modules, the port control modules being adapted for communication with the attached devices, the port control module functioning to build a route request and read a route response,

10

a router module, the router module being connected to the port control modules by a route request connection and by a separate route response connection, and

a single switch core supporting each of Class 1, Class 2 and Class 3 service, the switch core being connected to the port control modules.

15

**THIS PAGE BLANK (USPTO)**